

# Output Plug List










SA06N12-A-




























A1

A

A

Cable with ferrite core

Plug No.	Plug Name	I.D.	O.D.	Length	Plug Outline
1	Hollow Plug	1.35	3.5	6-12	 Hollow Plug
2		2.1	5.5	7-10	
3		2.1	5.5	10.5-14	
4	Hollow Plug R/A	1.35	3.5	6-12	 Hollow Plug R/A
5		2.1	5.5	7-10	
6		2.1	5.5	10.5-14	
7	Hollow Plug	2.5	5.5	8-14	
8	Hollow Plug R/A	2.5	5.5	8-14	
A1	EIAJ-1	0.7	2.35	6-12	
A1R	EIAJ-1 R/A	0.7	2.35	6-12	
A2	EIAJ-2	1.7	4.0	7-12	
A2R	EIAJ-2 R/A	1.7	4.0	7-12	
A3	EIAJ-3	1.7	4.75	7-12	
A3R	EIAJ-3 R/A	1.7	4.75	7-12	
A4	EIAJ-4	1.0/3.3	5.5	9.5	
A4R	EIAJ-4 R/A	1.0/3.3	5.5	9.5	
A5	EIAJ-5	1.37/4.4	6.5	9.5	
A5R	EIAJ-5 R/A	1.37/4.4	6.5	9.5	
B1	MOLEX 3.96mm	3 Pin			  3P    4P    5P    6P
B2		4 Pin			
B3		5 Pin			
B4		6 Pin			
C1	RJ Series	4 Pin			  4P    6P    8P
C2		6 Pin			
C3		8 Pin			

D1	Mini-DIN (male)	3 Pin	 	
D2		4 Pin		
D3		5 Pin		
D4		6 Pin		    
D5		7 Pin		3P 4P 5P 6P 7P
D6		8 Pin		
E1	Power Mini-DIN (male)	3 Pin	  	
E2		4 Pin		3P 4P
F1	DIN (male)	3 Pin	  	
F2		4 Pin		
F3		5 Pin		
F4		5 Pin-1		    
F5		6 Pin		3P 4P 5P 5P-1 6P
F6		7 Pin		
F7		8 Pin		
T	Interchangeable	2 Pin	 	
USB	USB	4 Pin	 	
SUSB	Mini-USB	4 Pin	 	
MUSB	Mini-USB	5 Pin	 	
Tinned	Strip&Tinned	---		

\* Special plugs are available, please ask for details.



**Autec Power Systems, Inc.**

Tel: 805-522-0888 Fax: 805-522-8777

e-mail: autecsales@autec.com

Web site www.Autec.com